

Stochastic expansions and Hopf algebras

BY SIMON J.A. MALHAM AND ANKE WIESE

*Maxwell Institute for Mathematical Sciences and School of Mathematical and
Computer Sciences, Heriot-Watt University, Edinburgh EH14 4AS, UK*

Dedicated to Mrs Jeanne Anne Malham

(17th April 2009)

We study solutions to nonlinear stochastic differential systems driven by a multi-dimensional Wiener process. A useful algorithm for strongly simulating such stochastic systems is the Castell–Gaines method, which is based on the exponential Lie series. When the diffusion vector fields commute, it has been proved that at low orders this method is more accurate in the mean-square error than corresponding stochastic Taylor methods. However it has also been shown that when the diffusion vector fields do not commute, this is not true for strong order one methods. Here we prove that when there is *no* drift, and the diffusion vector fields do not commute, the exponential Lie series is usurped by the sinh-log series. In other words, the mean-square error associated with a numerical method based on the sinh-log series, is always smaller than the corresponding stochastic Taylor error, in fact to *all* orders. Our proof utilizes the underlying Hopf algebra structure of these series, and a two-alphabet associative algebra of shuffle and concatenation operations. We illustrate the benefits of the proposed series in numerical studies.

Keywords: Stochastic expansions, Hopf algebras, numerical approximation

1. Introduction

We are interested in designing strong series solutions of nonlinear Stratonovich stochastic differential systems of the form

$$y_t = y_0 + \sum_{i=1}^d \int_0^t V_i(y_\tau) dW_\tau^i.$$

Here $(W^1, \dots, W^d)$ is a d -dimensional Wiener process and $y_t \in \mathbb{R}^N$ for some $N \in \mathbb{N}$ and all $t \in \mathbb{R}_+$. We suppose that $V_i: \mathbb{R}^N \rightarrow \mathbb{R}^N$, $i = 1, \dots, d$, are smooth non-commuting vector fields which in coordinates are $V_i = \sum_{j=1}^N V_i^j \partial_{y_j}$. Repeated iteration of the chain rule reveals the stochastic Taylor expansion for the solution to the stochastic differential system. Indeed for any smooth function $f: \mathbb{R}^N \rightarrow \mathbb{R}$ we have the formal stochastic Taylor series expansion

$$f \circ y_t = f \circ y_0 + \sum_{w \in \mathbb{A}^+} J_w(t) V_w \circ f \circ y_0.$$

Here $\mathbb{A}^+$ is the collection of non-empty words over the alphabet $\mathbb{A} = \{1, \dots, d\}$. We adopt the standard notation for Stratonovich integrals, if $w = a_1 \dots a_n$ then

$$J_w(t) = \int_0^t \dots \int_0^{\tau_{n-1}} dW_{\tau_n}^{a_1} \dots dW_{\tau_1}^{a_n}.$$

We have also written the composition of the vector fields as $V_w \equiv V_{a_1} \circ V_{a_2} \circ \dots \circ V_{a_n}$. We define the flow-map φ_t as the map such that

$$\varphi_t \circ f \circ y_0 = f \circ y_t.$$

It has a formal stochastic Taylor expansion of the form

$$\varphi_t = \text{id} + \sum_{w \in \mathbb{A}^+} J_w(t) V_w.$$

Note that $\varphi_t \circ \varphi_s = \varphi_{t+s}$ for all non-negative t, s and $\varphi_0 = \text{id}$, the identity mapping.

Classical strong numerical methods are based on truncating the stochastic Taylor expansion for the flow-map and applying the resulting approximate flow-map $\hat{\varphi}_t$ over successive small subintervals of the global interval of integration required (see Kloeden and Platen 1999 or Milstein 1994). An important and expensive ingredient in all numerical methods is the strong simulation/approximation of the required retained multiple integrals $J_w(t)$, on each integration step. Here we will take their suitable approximation as granted (see, for example, Wiktorsson 2001 for their practical simulation). Now let $F: \text{Diff}(\mathbb{R}^N) \rightarrow \text{Diff}(\mathbb{R}^N)$ be a smooth function. We can also construct flow approximations from φ_t via the following procedure.

- Construct the new series $\psi_t = F(\varphi_t)$.
- Truncate this series to produce the finite expansion $\hat{\psi}_t$.
- Reconstruct an approximate flow-map as $\hat{\varphi}_t = F^{-1}(\hat{\psi}_t)$.
- The “flow error” is the flow remainder $R_t = \varphi_t - \hat{\varphi}_t$.
- An approximate solution is given by $\hat{y}_t = \hat{\varphi}_t \circ y_0$.
- The mean-square error in this approximation is $\|R_t \circ y_0\|_{L^2}^2$.

For the special case $F = \log$, i.e. the logarithm function, this procedure was outlined by Castell and Gaines (1996). The resulting series $\psi_t = \log \varphi_t$ is the exponential Lie series, which lies in $\mathbb{R}\langle V_1, \dots, V_d \rangle$, the non-commutative algebra of formal series generated by the vector fields $V_1, \dots, V_d$. Indeed any truncation $\hat{\psi}_t$, with multiple integrals replaced by suitable approximations, also lies in $\mathbb{R}\langle V_1, \dots, V_d \rangle$ and is therefore a vector field. Hence $\hat{\varphi}_t = \exp \hat{\psi}_t$ and an approximation $\hat{y}_t$ to the solution can be constructed by solving the ordinary differential system for $u = u(\tau)$:

$$u' = \hat{\psi}_t \circ u$$

for $\tau \in [0, 1]$ with $u(0) = y_0$. The solution to this system at time $\tau = 1$, itself approximated by an ordinary differential numerical method, is $u(1) \approx \hat{y}_t$.

So far, what has been proved for the Castell–Gaines method? Castell and Gaines (1995, 1996) prove that the strong order one-half method constructed in this way is always more accurate than the Euler–Maruyama method. Indeed they prove that this method is *asymptotically efficient* in the sense of Newton (1991). Further in the case of a single driving Wiener process ($d = 1$), they prove the same is true for the strong order one Castell–Gaines method. By asymptotically efficient we mean, quoting from Newton (1991), that they “minimize the leading coefficient in the expansion of mean-square errors as power series in the sample step size”. Lord, Malham and Wiese (2008) and Malham and Wiese (2008) proved that when the diffusion vector fields *commute*, but not necessarily with the drift vector field, then the strong order one and also three-halves Castell–Gaines methods have a

mean-square error that is smaller than the mean-square error for the corresponding stochastic Taylor method. However Lord, Malham and Wiese (2008) also prove that for linear diffusion vector fields which do not commute, the strong order one Castell–Gaines method does not necessarily have a smaller mean-square error than the corresponding stochastic Taylor method. Indeed there are regions in the phase space where the local error of the stochastic Taylor method is smaller.

Hence we are left with the following natural question when the diffusion vector fields do not commute. Is there a solution series ansatz $\psi_t = F(\varphi_t)$ for some function F , for which the mean-square error of the numerical method so constructed, is always smaller than the corresponding stochastic Taylor method? In this paper we answer this question, indeed under the assumption there is *no drift*, we:

- (1) Prove the mean-square error of an approximate solution constructed from the *sinh-log* expansion (with $F = \sinh \log$ above) is smaller than that for the stochastic Taylor expansion, *to all orders*.
- (2) Prove that a numerical method based on the sinh-log expansion has a global error that is smaller than that for the corresponding stochastic Taylor method.
- (3) Utilize the Hopf shuffle algebra of words underlying such expansions; in fact we retract to a *new* associative algebra of concatenation and shuffle operators, that acts on the Hopf shuffle algebra of words.
- (4) Underpin our theoretical results with concrete numerical simulations.

We examine and interpret these statements in detail next, in Section 2, where we answer the following immediate questions. First, what precisely, is the sinh-log approximation and the properties we prove for it? Second, how do we prove the result; what is the connection with Hopf shuffle algebras and the concatenation-shuffle operator algebra mentioned? In Section 3 we provide the technical specification of the concatenation-shuffle operator algebra and prove some polynomial identities important for our main result. In Section 4 we present our main result. Then in Section 5 we discuss the global error result above, and perform numerical simulations confirming our results. We give some concluding remarks in Section 6.

2. Principal ideas

The goal of this section is to motivate and make precise statements about the sinh-log approximation we propose.

(a) Stochastic series expansion approximations

We begin by outlining the approximation procedure presented in the introduction in more detail. Suppose the smooth function F has a real series expansion of the form

$$F(x) = \sum_{k=1}^{\infty} C_k (x - 1)^k,$$

with some finite radius of convergence about $x = 1$, and for some coefficient set $\{C_k : k \geq 1\}$ with $C_1 = 1$. Given the flow-map φ_t , we construct the series

$$\psi_t = F(\varphi_t) \equiv \sum_{k=1}^{\infty} C_k (\varphi_t - \text{id})^k.$$

We substitute, into this series expansion, the stochastic Taylor series for the flow-map φ_t . After rearrangement, we get

$$\psi_t = \sum_{w \in \mathbb{A}^+} K_w(t) V_w,$$

where

$$K_w(t) = \sum_{k=1}^{|w|} C_k \sum_{\substack{u_1, \dots, u_k \in \mathbb{A}^+ \\ u_1 u_2 \dots u_k = w}} J_{u_1} J_{u_2} \dots J_{u_k}(t).$$

We truncate the series, dropping all terms V_w with words w of length $|w| \geq n+1$. This generates the approximation $\hat{\psi}_t$, once we have replaced all retained multiple integrals $J_u(t)$ by suitable approximations. Then, in principle, we construct the solution approximation $\hat{y}_t$ from $\hat{y}_t = \hat{\varphi}_t \circ y_0$, where

$$\hat{\varphi}_t = F^{-1}(\hat{\psi}_t).$$

Performing this reconstruction is nontrivial in general (see Section 5).

For example, to construct the exponential Lie series approximation of Castell and Gaines (1995), we take $F = \log$ and construct the series

$$\psi_t = \log \varphi_t \equiv \sum_{k=1}^{\infty} C_k (\varphi_t - \text{id})^k,$$

where $C_k = \frac{1}{k}(-1)^{k-1}$ for $k \geq 1$. Substituting the stochastic Taylor series for φ_t , the series expansion for ψ_t above becomes the exponential Lie series (see Strichartz 1987, Ben Arous 1989, Castell 1993 or Baudoin 2004 for the full series)

$$\psi_t = \sum_{w \in \mathbb{A}^+} K_{[w]}(t) V_{[w]}$$

where for $w = a_1 \dots a_n$ we have $V_{[w]} = [V_{a_1}, [V_{a_2}, \dots, [V_{a_{n-1}}, V_{a_n}] \dots]]$ and

$$K_{[w]} = \sum_{\sigma \in \mathbb{G}_{|w|}} \frac{(-1)^{e(\sigma)}}{|w|^2 D_{e(\sigma)}^{|w|-1}} J_{\sigma^{-1} \circ w}.$$

Here $\mathbb{G}_{|w|}$ is the group of permutations of the index set $\{1, \dots, |w|\}$, $e(\sigma)$ is the cardinality of the set $\{j \in \{1, \dots, |w|-1\} : \sigma(j) > \sigma(j+1)\}$, and $D_{e(\sigma)}^{|w|-1}$ is the combinatorial number: $|w|-1$ choose $e(\sigma)$. Truncating this series and using suitable approximations for the retained $J_{\sigma^{-1} \circ w}$, produces $\hat{\psi}_t$. We then reconstruct the solution approximately using $\hat{\varphi}_t = \exp \hat{\psi}_t$. The actual solution approximation $\hat{y}_t = \hat{\varphi}_t \circ y_0$ is then computed by solving the ordinary differential equation generated by the vector field $\hat{\psi}_t$.

To construct the sinh-log approximation, we take $F = \sinh \log$ so that

$$\psi_t = \sinh \log \varphi_t \equiv \frac{1}{2}(\varphi_t - \varphi_t^{-1}) \equiv \sum_{k=1}^{\infty} C_k (\varphi_t - \text{id})^k,$$

where $C_1 = 1$ and $C_k = \frac{1}{2}(-1)^{k-1}$ for $k \geq 2$. Again substituting the stochastic Taylor series for φ_t we get the series expansion for ψ_t shown above with terms $K_w(t)V_w$ where the coefficients $K_w(t)$ now explicitly involve the sinh-log coefficients C_k . Then, in principle, we can reconstruct the solution approximately using

$$\hat{\varphi}_t = \exp \sinh^{-1}(\hat{\psi}_t) \equiv \hat{\psi}_t + \sqrt{\text{id} + \hat{\psi}_t^2}.$$

Remark 2.1. Suppose the vector fields V_i , $i = 1, \dots, d$ are sufficiently smooth and t sufficiently small (but finite). Then the approximation $\hat{\varphi}_t \circ y_0$ constructed using the sinh-log expansion, as just described, is square-integrable. Further if y is the exact solution of the stochastic differential equation, and $\hat{\varphi}_t$ includes all terms $K_w V_w$ involving words of length $w \leq n$, then there exists a constant $C(n, |y|)$ such that $\|y_t - \hat{\varphi}_t \circ y_0\|_{L^2} \leq C(n, |y|) t^{(n+1)/2}$; here $|\cdot|$ is the Euclidean norm. This follows by arguments exactly analogous to those for the exponential Lie series given in Malham & Wiese (2008; Theorem 7.1 and Appendix A).

Remark 2.2. Naturally, the exponential Lie series ψ_t and its truncation $\hat{\psi}_t$ lie in the Lie algebra of vector fields generated by $V_1, \dots, V_d$. Hence $\exp(\tau \hat{\psi}_t)$ is simply the ordinary flow-map associated with the autonomous vector field $\hat{\psi}_t$.

Remark 2.3. The exponential Lie series originates with Magnus (1954) and Chen (1957); see Iserles (2002). In stochastic approximation it appears in Kunita (1980), Fleiss (1981), Azencott (1982), Strichartz (1987), Ben Arous (1989), Castell (1993), Castell & Gaines (1995, 1996), Lyons (1998), Burrage & Burrage (1999), Baudoin (2004), Lord, Malham & Wiese (2009) and Malham & Wiese (2008).

(b) Hopf algebra of words

Examining the coefficients K_w in the series expansion for ψ above, we see that they involve linear combinations of products of multiple Stratonovich integrals (we suspend explicit t dependence momentarily). The question is, can we determine K_w explicitly? Our goal here is to reduce this problem to a pure combinatorial one. This involves the Hopf algebra of words (see Reutenauer 1993).

Let $\mathbb{K}$ be a commutative ring with unit. In our applications we take $\mathbb{K} = \mathbb{R}$ or $\mathbb{K} = \mathbb{J}$, the ring generated by multiple Stratonovich integrals and the constant random variable 1, with pointwise multiplication and addition. Let $\mathbb{K}\langle\mathbb{A}\rangle$ denote the set of all noncommutative polynomials and formal series on the alphabet $\mathbb{A} = \{1, 2, \dots, d\}$ over $\mathbb{K}$. With the concatenation product, $\mathbb{K}\langle\mathbb{A}\rangle$ is the associative *concatenation algebra*. For any two words $u, v \in \mathbb{K}\langle\mathbb{A}\rangle$ with lengths $|u|$ and $|v|$, we define the *shuffle product* $u \sqcup v$ to be the sum of the words of length $|u| + |v|$ created by shuffling all the letters in u and v whilst preserving their original order. The shuffle product is extended to $\mathbb{K}\langle\mathbb{A}\rangle$ by bilinearity. It is associative, and distributive with respect to addition, and we obtain on $\mathbb{K}\langle\mathbb{A}\rangle$ a commutative algebra called the *shuffle algebra* (note $1 \sqcup w = w \sqcup 1 = w$ for any word w where 1 is the empty word). The linear signed reversal mapping $\alpha \in \text{End}(\mathbb{K}\langle\mathbb{A}\rangle)$:

$$\alpha \circ w = (-1)^n a_n \dots a_1,$$

for any word $w = a_1 \dots a_n$ is the *antipode* on $\mathbb{K}\langle\mathbb{A}\rangle$. There are two *Hopf algebra* structures on $\mathbb{K}\langle\mathbb{A}\rangle$, namely $(\mathbb{K}\langle\mathbb{A}\rangle, c, \delta, \eta, \varepsilon, \alpha)$ and $(\mathbb{K}\langle\mathbb{A}\rangle, s, \delta', \eta, \varepsilon, \alpha)$, where η and

ε are unit and co-unit elements, and δ and δ' respective co-products (Reutenauer, p. 27). We define the associative algebra using the complete tensor product

$$\mathcal{H} = \mathbb{K}\langle \mathbb{A} \rangle \overline{\otimes} \mathbb{K}\langle \mathbb{A} \rangle$$

with the shuffle product on the left and the concatenation product on the right (Reutenauer, p. 29). The product of elements $u \otimes x, v \otimes y \in \mathcal{H}$ is given by

$$(u \otimes x)(v \otimes y) = (u \sqcup v) \otimes (xy),$$

and formally extended to infinite linear combinations in $\mathcal{H}$ via linearity. As a tensor product of two Hopf algebra structures, $\mathcal{H}$ itself acquires a Hopf algebra structure.

(c) *Pullback to Hopf shuffle algebra*

Our goal is to pullback the flow-map φ and also ψ to $\mathcal{H}$ (with $\mathbb{K} = \mathbb{R}$). Let $\mathbb{V}$ be the set of all vector fields on $\mathbb{R}^N$; it is an $\mathbb{R}$ -module over $C^\infty(\mathbb{R}^N)$ (see Varadarajan 1984, p. 6). We know that for the stochastic Taylor series the flow-map $\varphi \in \mathbb{J}\langle \mathbb{V} \rangle$ (with vector field composition as product). Since $\mathbb{J}\langle \mathbb{V} \rangle \cong \bigoplus_{n \geq 0} \mathbb{J} \otimes \mathbb{V}_n$, where $\mathbb{V}_n$ is the subset of $\mathbb{V}$ of compositions of vector fields of length n , we can write

$$\varphi = 1 \otimes \text{id}_{\mathbb{V}} + \sum_{w \in \mathbb{A}^+} J_w \otimes V_w.$$

The linear *word-to-vector field map* $\kappa: \mathbb{R}\langle \mathbb{A} \rangle \rightarrow \mathbb{V}$ given by $\kappa: \omega \mapsto V_\omega$ is a concatenation homomorphism, i.e. $\kappa(uv) = \kappa(u)\kappa(v)$ for any $u, v \in \mathbb{A}^+$. And the linear *word-to-integral map* $\mu: \mathbb{R}\langle \mathbb{A} \rangle \rightarrow \mathbb{J}$ given by $\mu: \omega \mapsto J_\omega$ is a shuffle homomorphism, i.e. $\mu(u \sqcup v) = \mu(u)\mu(v)$ for any $u, v \in \mathbb{A}^+$ (see for example, Lyons, *et. al.* 2007, p. 35 or Reutenauer 1993, p. 56). Hence the map $\mu \otimes \kappa: \mathcal{H} \rightarrow \bigoplus_{n \geq 0} \mathbb{J} \otimes \mathbb{V}_n$ is a Hopf algebra homomorphism. The pullback of the flow-map φ by $\mu \otimes \kappa$ is

$$(\mu \otimes \kappa)^* \varphi = 1 \otimes 1 + \sum_{w \in \mathbb{A}^+} w \otimes w.$$

All the relevant information about the stochastic flow is encoded in this formal series; it is essentially Lyons' *signature* (see Lyons, Caruana and Lévy 2007; Baudoin 2004). Hence by direct computation, formally we have

$$\begin{aligned} (\mu \otimes \kappa)^* \psi &= \sum_{k \geq 1} C_k ((\mu \otimes \kappa)^* \varphi - 1 \otimes 1)^k \\ &= \sum_{k \geq 1} C_k \left(\sum_{w \in \mathbb{A}^+} w \otimes w \right)^k \\ &= \sum_{k \geq 1} C_k \left(\sum_{u_1, \dots, u_k \in \mathbb{A}^+} (u_1 \sqcup \dots \sqcup u_k) \otimes (u_1 \dots u_k) \right) \\ &= \sum_{w \in \mathbb{A}^*} \left(\sum_{k=1}^{|w|} C_k \sum_{\substack{u_1, \dots, u_k \in \mathbb{A}^+ \\ w = u_1 \dots u_k}} u_1 \sqcup \dots \sqcup u_k \right) \otimes w \\ &= \sum_{w \in \mathbb{A}^*} (K \circ w) \otimes w, \end{aligned}$$

where $K \circ w$ is defined by

$$K \circ w = \sum_{k=1}^{|w|} C_k \sum_{\substack{u_1, \dots, u_k \in \mathbb{A}^+ \\ w = u_1 \dots u_k}} u_1 \sqcup \dots \sqcup u_k,$$

corresponds to K_w (indeed it is the pullback $\mu^* K_w$ to $\mathbb{O}_w$; see Section 3). Having reduced the problem of determining $K \circ w$ to the algebra of shuffles, a further simplifying reduction is now possible.

Remark 2.4. The use of Hopf shuffle algebras in stochastic expansions can be traced through, for example, Strichartz (1987), Reutenauer (1993), Gaines (1994), Li & Liu (2000), Kawski (2001), Baudoin (2004), Murua (2005), Ebrahimi-Fard & Guo (2006), Manchon & Paycha (2006) and Lyons, Caruana & Lévy (2007), to name a few. The paper by Munthe-Kaas & Wright (2008) on the Hopf algebraic of Lie group integrators actually instigated the Hopf algebra direction adopted here. A useful outline on the use of Hopf algebras in numerical analysis can be found therein, as well as the connection to the work by Connes & Mischovici (1998) and Connes & Kreimer (1998) in renormalization in perturbative quantum field theory.

(d) *Retraction to concatenations and shuffles*

For any given word $w = a_1 \dots a_{n+1}$ we now focus on the coefficients $K \circ w$. We observe that it is the concatenation and shuffle operations encoded in the structural form of the sum for $K \circ w$ that carry all the relevant information. Indeed each term $u_1 \sqcup \dots \sqcup u_k$ is a partition of w into subwords that are shuffled together. Each subword u_i is a concatenation of $|u_i|$ letters, and so we can reconstruct each term of the form $u_1 \sqcup \dots \sqcup u_k$ from the following sequence applied to the word w :

$$c^{|u_1|-1} s c^{|u_2|-1} s \dots s c^{|u_k|-1}$$

where the power of the letter c indicates the number of letters concatenated together in each subword u_i and the letter s denotes the shuffle product between the subwords. In other words, if we factor out the word w , we can replace $K \circ w$ by a polynomial K of the letters c and s . In fact, in Lemma 3.3 we show that

$$K = \sum_{k=0}^n C_{k+1} (c^{n-k} \sqcup s^k).$$

Thus we are left with the task of simplifying this polynomial in two variables (lying in the real associative algebra of concatenation and shuffle operations).

Remark 2.5. We devote Section 3 to the rigorous justification of this retraction, the result above, and those just following. A key ingredient is to identify the correct action of this algebra over $(\mathbb{K}\langle\mathbb{A}\rangle, s, \alpha)$.

Remark 2.6. There is a natural right action by the symmetric group $\mathbb{S}_n$ on $\mathbb{K}\langle\mathbb{A}\rangle_n$, the subspace of $\mathbb{K}\langle\mathbb{A}\rangle$ spanned by words of length n (Reutenauer 1993, Chapter 8). This action is transitive and extends by linearity to a right action of the group algebra $\mathbb{K}\langle\mathbb{S}_n\rangle$ on $\mathbb{K}\langle\mathbb{A}\rangle_n$. We are primarily concerned with shuffles and multi-shuffles, a subclass of operations in $\mathbb{K}\langle\mathbb{S}_n\rangle$, and in particular, we want a convenient structure that enables us to combine single shuffles to produce multi-shuffles.

(e) *Stochastic sinh-log series coefficients*

The coefficient set $\{C_k : k \geq 1\}$ determines the form of the function F . Our ultimate goal is to show order by order that the stochastic sinh-log expansion guarantees superior accuracy. Hence order by order we allow a more general coefficient set $\{C_k : k \geq 1\}$, and show that the sinh-log choice provides the guarantee we seek.

Definition 2.1 (Partial sinh-log coefficient set). *Define the partial sinh-log coefficient sequence:*

$$C_k = \begin{cases} 1, & k = 1, \\ \frac{1}{2}(-1)^{k-1}, & k \geq 2, \\ \frac{1}{2}(-1)^n + \epsilon, & k = n + 1, \end{cases}$$

where $\epsilon \in \mathbb{R}$.

With the choice of coefficients $\{C_k\}$, we see that

$$K = \frac{1}{2}c^n + \frac{1}{2} \sum_{k=0}^n (-1)^k (c^{n-k} \sqcup s^k) + \epsilon s^n.$$

This has an even simpler form.

Lemma 2.1. *With the partial sinh-log coefficient sequence $\{C_k\}$, the coefficient K is given by*

$$K = \frac{1}{2}(c^n - \alpha_n) + \epsilon s^n,$$

where α_n is the antipode for words of length $n + 1$.

Proof. We think of $(c - s)^n$, with expansion by concatenation, as the generator for the polynomial (in $\mathbb{K}\langle \mathbb{B} \rangle_n$; see Section 3) defined by

$$(c - s)^n = \sum_{k=0}^n (-1)^k (c^{n-k} \sqcup s^k).$$

Then by Lemma 3.2 in Section 3 we have the following identity

$$(c - s)^n \equiv -\alpha_n.$$

Hence using the sinh-log coefficients and splitting the first term, we have

$$\begin{aligned} K &= \frac{1}{2}c^n + \frac{1}{2} \sum_{k=0}^n (-1)^k (c^{n-k} \sqcup s^k) + \epsilon s^n \\ &= \frac{1}{2}c^n + \frac{1}{2}(c - s)^n + \epsilon s^n \\ &= \frac{1}{2}c^n - \frac{1}{2}\alpha_n + \epsilon s^n. \end{aligned}$$

□

Corollary 2.2. *For any word $w = a_1 \dots a_{n+1}$ we have*

$$K \circ w = \frac{1}{2}(w - \alpha \circ w) + \epsilon a_1 \sqcup \dots \sqcup a_{n+1},$$

and thus

$$K_w = \frac{1}{2}(J_w - J_{\alpha \circ w}) + \epsilon \prod_{i=1}^{n+1} J_{a_i}.$$

Remark 2.7. For the stochastic sinh-log expansion the coefficients K_w thus have an extremely simple form. There are several strategies to prove this form. The result can be proved directly in terms of multiple Stratonovich integrals by judicious use of their properties, the partial integration formula and induction—the proof is long but straightforward. That this strategy works is also revealed by the strategy we have adopted in this paper, which we believe is shorter and more insightful.

3. Concatenation-shuffle operator algebra

(a) Algebra and action

With $\mathbb{B} = \{c, s\}$, let $\mathbb{K}\langle\mathbb{B}\rangle$ denote the set of all noncommutative polynomials and formal series on $\mathbb{B}$ over $\mathbb{K}$. We can endow $\mathbb{K}\langle\mathbb{B}\rangle$ with the concatenation product or shuffle product, and also generate an associative *concatenation-shuffle operator algebra* on $\mathbb{K}\langle\mathbb{B}\rangle$ as follows.

Definition 3.1 (Shuffle gluing product). *The map $g: \mathbb{K}\langle\mathbb{B}\rangle \otimes \mathbb{K}\langle\mathbb{B}\rangle \rightarrow \mathbb{K}\langle\mathbb{B}\rangle$, the associative and bilinear shuffle gluing product, is defined by*

$$g: b_1 \otimes b_2 \mapsto b_1 s b_2,$$

i.e. we concatenate the element b_1 with s and the element b_2 in $\mathbb{K}\langle\mathbb{B}\rangle$ as shown.

Endowed with the shuffle gluing product, $\mathbb{K}\langle\mathbb{B}\rangle$ is an associative algebra with unit element s^{-1} (see Reutenauer 1993, p. 26, for the definition of s^{-1}). We define the graded associative tensor algebra $\mathcal{K}$ by

$$\mathcal{K} = \bigoplus_{n \geq 0} \mathbb{K}\langle\mathbb{B}\rangle_n \otimes \mathbb{K}\langle\mathbb{A}\rangle_{n+1},$$

with the shuffle gluing product on the left in $\mathbb{K}\langle\mathbb{B}\rangle_n$ and concatenation product on the right in $\mathbb{K}\langle\mathbb{A}\rangle_{n+1}$ —here $\mathbb{K}\langle\mathbb{B}\rangle_n$ and $\mathbb{K}\langle\mathbb{A}\rangle_{n+1}$ denote the subspaces of $\mathbb{K}\langle\mathbb{B}\rangle$ and $\mathbb{K}\langle\mathbb{A}\rangle$, respectively, spanned by words of length n and $n+1$, respectively. Thus if $b_1 \otimes u_1$ and $b_2 \otimes u_2$ are in $\mathcal{K}$ then their product is

$$(b_1 \otimes u_1)(b_2 \otimes u_2) = (b_1 s b_2) \otimes (u_1 u_2),$$

with extension to $\mathcal{K}$ by bilinearity.

We now define the homomorphism $\zeta: \mathcal{K} \rightarrow (\mathbb{K}\langle\mathbb{A}\rangle, s, \delta', \alpha)$ as follows. Any word $b \in \mathbb{B}^+$, for some $k \in \mathbb{N}$ and $n_1, \dots, n_k \in \mathbb{N} \cup \{0\}$, can be expressed in the form

$$b = c^{n_1} s c^{n_2} s c^{n_3} \dots s c^{n_k}.$$

There are $(k-1)$ occurrences of the symbol ‘ s ’ in b , and $n_1 + n_2 + \dots + n_k + k - 1 = |b|$. Here c^n represents the word consisting of c multiplied by concatenation n times, $c^0 = 1$; similarly for s^n and s^0 . Then we define

$$\zeta: b \otimes w \mapsto b \circ w = u_{n_1} \sqcup u_{n_2} \sqcup \dots \sqcup u_{n_k},$$

where $w = u_{n_1} u_{n_2} \dots u_{n_k}$ and the successive subwords $u_{n_1}, u_{n_2}, \dots, u_{n_k}$ have respective lengths $n_1 + 1, n_2 + 1, \dots, n_k + 1$. Note the sum of the lengths of the

subwords is $n + 1$. The map ζ extends by linearity to $\mathcal{K}$. The c -symbol indicates a concatenation product and the s -symbol a shuffle product in the appropriate n slots between the $n + 1$ letters in any word w on $\mathbb{A}^+$ of length $n + 1$. That ζ is a homomorphism from $\mathcal{K}$ to $\mathbb{K}\langle\mathbb{A}\rangle$ follows from:

$$\zeta((b_1 \otimes u_1)(b_2 \otimes u_2)) = \zeta((b_1 s b_2) \otimes (u_1 u_2)) = \zeta(b_1 \otimes u_1) \sqcup \zeta(b_2 \otimes u_2).$$

Definition 3.2 (Partition orbit). *We define the (shuffle) partition orbit, $\mathbb{O}(w)$, of a word $w \in \mathbb{A}^+$ to be the subset of $\mathbb{K}\langle\mathbb{A}\rangle$ whose elements are linear combinations of words constructed by concatenating and shuffling the letters of $w = a_1 \dots a_n$:*

$$\mathbb{O}(w) = \{\text{span}(u_1 \sqcup \dots \sqcup u_k) : u_1 \dots u_k = w; u_1, \dots, u_k \in \mathbb{A}^+; k \in \{1, \dots, |w|\}\}.$$

For any $u \in \mathbb{O}(w)$ there exists a $b \in \mathbb{K}\langle\mathbb{B}\rangle_{|w|-1}$ such that $u = \zeta(b \otimes w)$. Hence we can consider the preimage of $\mathbb{O}(w)$ under ζ in $\mathcal{K}$ given by $\zeta^{-1}\mathbb{O}(w) = \{b \otimes w \in \mathcal{K} : \zeta(b \otimes w) \in \mathbb{O}(w)\}$. Thus any element in $\mathbb{O}(w)$ can be identified with an element $b \otimes w \in \zeta^{-1}\mathbb{O}(w)$ for a unique $b \in \mathbb{K}\langle\mathbb{B}\rangle_{|w|-1}$ and there is a natural projection map

$$\pi : \mathbb{O}(w) \rightarrow \mathbb{K}\langle\mathbb{B}\rangle_{|w|-1}.$$

(b) Polynomial identities

Here we prove a sequence of lemmas that combine to prove our main results. The aim of the first two lemmas is to establish a form for the antipode α as a polynomial in the concatenation-shuffle operator algebra $(\mathbb{R}\langle\mathbb{B}\rangle, g)$. We shall denote the antipode in $\text{End}(\mathbb{R}\langle\mathbb{A}\rangle_{n+1})$ by α_n ; it sign reverses any word $w \in \mathbb{R}\langle\mathbb{A}\rangle_{n+1}$.

Lemma 3.1 (Partial integration formula). *The partial integration formula applied repeatedly to the multiple Stratonovich integral J_w , where $w = a_1 \dots a_{n+1}$, pulled back to $\mathbb{R}\langle\mathbb{B}\rangle_{|w|-1}$, is given by*

$$\alpha_n \equiv -c^n - \sum_{k=0}^{n-1} c^k s \alpha_{n-k-1}.$$

Proof. Repeated partial integration on the multiple Stratonovich integral J_w with $w = a_1 \dots a_{n+1}$, pulled back to $\mathbb{R}\langle\mathbb{A}\rangle_{n+1}$ via the word-to-integral map μ generates the identity:

$$a_1 \dots a_{n+1} = (a_1 \dots a_n) \sqcup a_{n+1} - (a_1 \dots a_{n-1}) \sqcup (a_{n+1} a_n) + \dots + (-1)^n a_{n+1} \dots a_1.$$

After rearrangement, the projection of this identity in $\mathbb{O}(w)$ onto $\mathbb{R}\langle\mathbb{B}\rangle_n$ via π , using the definition for α_n , generates the identity shown. $\square$

Lemma 3.2 (Antipode polynomial). *The antipode $\alpha_n \in \text{End}(\mathbb{R}\langle\mathbb{A}\rangle_{n+1})$ and polynomial $-(c - s)^n \in \mathbb{K}\langle\mathbb{B}\rangle_n$ are the same linear endomorphism on $\mathbb{R}\langle\mathbb{A}\rangle_{n+1}$:*

$$\alpha_n \equiv -(c - s)^n.$$

Proof. The statement of the lemma is trivially true for $n = 1, 2$. We assume it is true for $k = 1, 2, \dots, n-1$. Direct expansion reveals that

$$(c-s)^n = c^n - \sum_{k=0}^{n-1} c^k s (c-s)^{n-k-1}.$$

By induction, using our assumption in this expansion and comparing with the partial integration formula in Lemma 3.1 proves the statement for $k = n$. $\square$

Lemma 3.3. *The projection of $K \circ w \in \mathbb{O}(w)$ onto $\mathbb{R}\langle \mathbb{B} \rangle_n$ via π generates*

$$K = \sum_{k=0}^n C_{k+1} (c^{n-k} \sqcup s^k).$$

Proof. For any $w \in \mathbb{A}^+$ with $|w| = n+1$ we have

$$\begin{aligned} K \circ w &= \sum_{k=1}^{n+1} C_k \zeta((c^{n-(k-1)} \sqcup s^{k-1}) \otimes w) \\ &= \sum_{k=0}^n C_{k+1} \zeta((c^{n-k} \sqcup s^k) \otimes w) \\ &= \zeta\left(\left(\sum_{k=0}^n C_{k+1} (c^{n-k} \sqcup s^k)\right) \otimes w\right). \end{aligned}$$

Projecting this onto $\mathbb{R}\langle \mathbb{B} \rangle_n$ establishes the result. $\square$

4. Mean-square sinh-log remainder is smaller

Suppose the *flow remainder* associated with a flow approximation $\hat{\varphi}_t$ is

$$R_t := \varphi_t - \hat{\varphi}_t.$$

The remainder associated with the approximation $\hat{y}_t = \hat{\varphi}_t \circ y_0$ is thus $R_t \circ y_0$. We measure the error in this approximation, for each $y_0 \in \mathbb{R}^N$, in mean-square by

$$\|R_t \circ y_0\|_{L^2}^2 = \mathbb{E}((R_t \circ y_0)^T (R_t \circ y_0)).$$

If we truncate $\psi = F(\varphi)$ to $\hat{\psi}$, including all terms V_w with words of length $|w| \leq n$, suppose the remainder is r , i.e. we have

$$\psi = \hat{\psi} + r.$$

Then the remainder to the corresponding approximate flow $\hat{\varphi}^{\text{sl}} = F^{-1}(\hat{\psi})$, taking the difference with the exact stochastic Taylor flow φ^{st} , is given by

$$\begin{aligned} R^{\text{sl}} &= \varphi^{\text{st}} - \hat{\varphi}^{\text{sl}} \\ &= F^{-1}(\psi) - F^{-1}(\hat{\psi}) \\ &= F^{-1}(\hat{\psi} + r) - F^{-1}(\hat{\psi}) \\ &= r - C_2(r\hat{\psi} + \hat{\psi}r) + \mathcal{O}(\hat{\psi}^2 r), \end{aligned}$$

where we can ignore the $C_2(r\hat{\psi}+\hat{\psi}r)$ and $\mathcal{O}(\hat{\psi}^2r)$ terms in this section—we comment on their significance in Section 5. We compare this with the stochastic Taylor flow remainder $R^{\text{st}} := \varphi^{\text{st}} - \hat{\varphi}^{\text{st}}$, where $\hat{\varphi}^{\text{st}}$ is the stochastic Taylor flow series truncated to include all terms V_w with words of length $|w| \leq n$. Indeed, we set

$$\bar{R} := R^{\text{st}} - R^{\text{sl}},$$

and use the L^2 norm to measure the remainder. Hence for any data y_0 , we have

$$\|R^{\text{st}} \circ y_0\|_{L^2}^2 = \|R^{\text{sl}} \circ y_0\|_{L^2}^2 + E,$$

where the *mean-square excess*

$$E := \mathbb{E} (\bar{R} \circ y_0)^{\text{T}} (R^{\text{sl}} \circ y_0) + \mathbb{E} (R^{\text{sl}} \circ y_0)^{\text{T}} (\bar{R} \circ y_0) + \mathbb{E} (\bar{R} \circ y_0)^{\text{T}} (\bar{R} \circ y_0).$$

If E is positive then $R^{\text{sl}} \circ y_0$ is smaller than $R^{\text{st}} \circ y_0$ in the L^2 norm.

Theorem 4.1. *Suppose we construct the finite sinh-log expansion ψ using the partial sequence of sinh-log coefficients $\{C_k\}$, and truncate ψ producing $\hat{\psi}$ which only includes terms with words w with $|w| \leq n$. Then the flow remainders for the sinh-log and the corresponding stochastic Taylor approximations are such that, for any data y_0 and order $n \in \mathbb{N}$, the mean-square excess is given by*

$$E = E_0 - \epsilon E_1 - \epsilon^2 E_2,$$

where $E_0 > 0$, $E_2 > 0$ and

$$E_1 = \begin{cases} \hat{E}_1, & \text{if } n \text{ even,} \\ 0, & \text{if } n \text{ odd,} \end{cases}$$

where, for n even, we have

$$\hat{E}_1 = \sum_{\substack{u, v \in \mathbb{A}^+ \\ |u|=|v|=n+1}} \xi(u, v) (V_u \circ y_0)^{\text{T}} (V_v \circ y_0),$$

and

$$\xi(u, v) = \mathbb{E} \left(\frac{1}{2} (J_u + J_{\rho \circ u}) \prod_{i=1}^{n+1} J_{v_i} + \frac{1}{2} (J_v + J_{\rho \circ v}) \prod_{i=1}^{n+1} J_{u_i} \right) > 0.$$

Here ρ is the unsigned reversal mapping, i.e. if $w = a_1 \dots a_n$ then $\rho \circ w = a_n \dots a_1$.

Proof. If we truncate the sinh-log series flow-map including all integrals associated with words of length n , the remainder is given by

$$R^{\text{sl}} = \sum_{\substack{w \in \mathbb{A}^+ \\ |w| \geq n+1}} K_w V_w + \dots,$$

where henceforth we will ignore integrals in the remainder with $|w| \geq n+2$. Recall that from Corollary 2.2 we have

$$K_w = \frac{1}{2} (J_w - J_{\alpha \circ w}) + \epsilon \prod_{i=1}^{n+1} J_{w_i}.$$

The corresponding stochastic Taylor flow-map remainder is

$$\sum_{\substack{w \in \mathbb{A}^+ \\ |w|=n+1}} J_w V_w.$$

The difference between the two is

$$\bar{R} = \sum_{\substack{w \in \mathbb{A}^+ \\ |w|=n+1}} \bar{J}_w V_w,$$

where $\bar{J}_w = J_w - K_w$ and is given by

$$\bar{J}_w = \frac{1}{2}(J_w + J_{\alpha \circ w}) - \epsilon \prod_{i=1}^{n+1} J_{w_i}.$$

The mean-square excess to the sinh-log remainder is E which at leading order is

$$\sum_{\substack{u, v \in \mathbb{A}^+ \\ |u|=|v|=n+1}} \mathbb{E}(\bar{J}_u K_v + K_u \bar{J}_v + \bar{J}_u \bar{J}_v) (V_u \circ y_0)^T (V_v \circ y_0).$$

We need to determine whether this quantity is positive definite or not. We refer to $\bar{J}_u K_v + K_u \bar{J}_v$ as the *cross-correlation* terms and $\bar{J}_u \bar{J}_v$ as the *auto-correlation* terms. The forms for K_u and $\bar{J}_u$ imply that:

$$\begin{aligned} \bar{J}_u K_v + K_u \bar{J}_v + \bar{J}_u \bar{J}_v &= \epsilon^0 \left(\frac{1}{2}(J_u J_v - J_{\alpha \circ u} J_{\alpha \circ v}) + \frac{1}{4}(J_u + J_{\alpha \circ u})(J_v + J_{\alpha \circ v}) \right) \\ &\quad - \epsilon^1 \left(\frac{1}{2}(J_u - J_{\alpha \circ u}) \prod_{i=1}^{n+1} J_{v_i} + \frac{1}{2}(J_v - J_{\alpha \circ v}) \prod_{i=1}^{n+1} J_{u_i} \right) \\ &\quad - \epsilon^2 \left(\prod_{i,j=1}^{n+1} J_{u_i} J_{v_j} \right). \end{aligned}$$

Consider the zero order ϵ^0 term. Using Lemma 4.3, the expectation of the cross-correlation term therein (the first term on the right above) is zero. Hence we have

$$\begin{aligned} E_0 &= \sum_{\substack{u, v \in \mathbb{A}^+ \\ |u|=|v|=n+1}} \mathbb{E} \left(\frac{1}{4}(J_u + J_{\alpha \circ u})(J_v + J_{\alpha \circ v}) \right) (V_u \circ y_0)^T (V_v \circ y_0) \\ &= \mathbb{E} \left(\sum_{|u|=n+1} \frac{1}{2}(J_u + J_{\alpha \circ u}) (V_u \circ y_0) \right)^T \left(\sum_{|v|=n+1} \frac{1}{2}(J_v + J_{\alpha \circ v}) (V_v \circ y_0) \right) \\ &> 0. \end{aligned}$$

At the next order ϵ^1 , the terms shown are solely from cross-correlations—with the auto-correlation terms cancelling with other cross-correlation terms. When n is odd the expectation of this term is zero, again using Lemma 4.3. When n is even we

get the expression for E_1 stated in the theorem. Finally at order ϵ^2 the coefficient shown is the auto-correlation term multiplied by minus one. Explicitly we see that

$$\begin{aligned} E_2 &= \sum_{\substack{u,v \in \mathbb{A}^+ \\ |u|=|v|=n+1}} \mathbb{E} \left(\prod_{i,j=1}^{n+1} J_{u_i} J_{v_j} \right) (V_u \circ y_0)^T (V_v \circ y_0) \\ &= \mathbb{E} \left(\sum_{|u|=n+1} \prod_{i=1}^{n+1} J_{u_i} (V_u \circ y_0) \right)^T \left(\sum_{|v|=n+1} \prod_{j=1}^{n+1} J_{v_j} (V_v \circ y_0) \right) \\ &> 0. \end{aligned}$$

Combining these results generates the form for E stated. $\square$

Corollary 4.2. *When n is odd, E is positive and maximized when $\epsilon = 0$. When n is even, it is positive at $\epsilon = 0$, but maximized at a different value of ϵ ; the maximizing value will depend on the vector fields.*

Lemma 4.3. *For any pair $u, v \in \mathbb{A}^+$ we have that*

$$\mathbb{E}(J_u J_v - J_{\rho \circ u} J_{\rho \circ v}) = 0.$$

Proof. Every Stratonovich integral J_w is a linear combination of Itô integrals

$$J_w = \sum_{u \in \mathbb{D}(w)} c_u I_u,$$

where the set $\mathbb{D}(w)$ consists of w and all multi-indices u obtained by successively replacing any two adjacent (non-zero) equal indices in w by 0, see Kloeden and Platen (1999), equation (5.2.34). Since all indices in w are non-zero by assumption, the constant c_u is given by

$$c_u = \left(\frac{1}{2}\right)^{n(u)},$$

where $n(u)$ denotes the number of zeros in u . Since adjacency is retained when reversing an index, it follows that

$$J_{\rho \circ w} = \sum_{u \in \mathbb{D}(w)} c_u I_{\rho \circ u}.$$

Lemma 5.7.2 in Kloeden and Platen (1999) implies that the expected value of the product of two multiple Itô integrals is of the form

$$\mathbb{E}(I_u I_v) = f \left(\ell(u), \ell(v), \sum_{i=0}^{\ell(u)} (k_i(u) + k_i(v)), \prod_{i=0}^{\ell(u)} \frac{(k_i(u) + k_i(v))!}{k_i(u)! k_i(v)!} \right)$$

for some function f . Here $\ell(u)$ denotes the number of non-zero indices in u , while $k_0(u)$ denotes the number of zero components preceding the first non-zero component of u , and $k_i(u)$, for $i = 1, \dots, \ell(u)$, the number of components of u between the i -th and $(i+1)$ -th non-zero components, or the end of u if $i = \ell(u)$. It follows that

$$k_i(u) = k_{\ell(u)-i}(\rho \circ u).$$

Since all other operations in the arguments of f are unchanged by permutations in u and v , we deduce that

$$\mathbb{E}(I_u I_v) = \mathbb{E}(I_{\rho \circ u} I_{\rho \circ v}),$$

and consequently,

$$\mathbb{E}(J_u J_v - J_{\rho \circ u} J_{\rho \circ v}) = \sum_{\substack{u' \in \mathbb{D}(u) \\ v' \in \mathbb{D}(v)}} c_{u'} c_{v'} \mathbb{E}(I_{u'} I_{v'} - I_{\rho \circ u'} I_{\rho \circ v'}) = 0.$$

□

5. Practical implementation

(a) Global error

We define the *strong global error* associated with an approximate solution $\hat{y}_T$ over the global interval $[0, T]$ as $\mathcal{E} := \|y_T - \hat{y}_T\|_{L^2}$. Suppose the exact y_T and approximate solution $\hat{y}_T$ are constructed by successively applying the exact and approximate flow-maps $\varphi_{t_m, t_{m+1}}$ and $\hat{\varphi}_{t_m, t_{m+1}}$ on M successive intervals $[t_m, t_{m+1}]$, with $t_m = mh$ for $m = 0, 1, \dots, M-1$ and $h = T/M$ as the fixed stepsize, to the initial data y_0 . A straightforward calculation shows that up to higher order terms we have

$$\mathcal{E}^2 = \mathbb{E}(\mathcal{R} \circ y_0)^T (\mathcal{R} \circ y_0),$$

where

$$\mathcal{R} \circ y_0 \equiv \sum_{m=0}^{M-1} \hat{\varphi}_{t_{m+1}, t_M} \circ R_{t_m, t_{m+1}} \circ \hat{\varphi}_{t_0, t_m},$$

and $R_{t_m, t_{m+1}} := \varphi_{t_m, t_{m+1}} - \hat{\varphi}_{t_m, t_{m+1}}$ (see Lord, Malham and Wiese 2008 or Malham and Wiese 2008). Note that the flow remainder $R_{t_m, t_{m+1}}$ always has the form

$$R_{t_m, t_{m+1}} = \sum_{|w| \geq n+1} \tilde{K}_w(t_m) V_w,$$

where for the sinh-log series $\tilde{K}_w = \frac{1}{2}(J_w - J_{\alpha \circ w})$, for the exponential Lie series $\tilde{K}_w = K_{[w]}$ (for each term in the linear combination $V_{[w]}$) and for the stochastic Taylor series $\tilde{K}_w = J_w$. Substituting this into $\mathcal{R}$ we see that $\mathcal{E}^2$ has the form

$$\mathcal{E}^2 = \sum_{\substack{|u| \geq n+1 \\ |v| \geq n+1}} \left(\sum_m \mathcal{V}_{m,m}(u, v) + \sum_{\ell \neq m} \mathcal{V}_{\ell,m}(u, v) \right),$$

where

$$\mathcal{V}_{\ell,m}(u, v) = \mathbb{E}(\hat{\varphi}_{t_{\ell+1}, t_M} \circ \tilde{K}_u(t_\ell) V_u \circ \hat{\varphi}_{t_0, t_\ell} \circ y_0)^T (\hat{\varphi}_{t_{m+1}, t_M} \circ \tilde{K}_v(t_m) V_v \circ \hat{\varphi}_{t_0, t_m} \circ y_0).$$

This formula outlines the contribution of the standard accumulation of local errors, over successive subintervals of the global interval of integration, to the global error. Note that to leading order we have

$$\mathcal{V}_{m,m}(u, v) = \mathbb{E}(\tilde{K}_u(t_m) \tilde{K}_v(t_m)) (V_u \circ y_0)^T (V_v \circ y_0).$$

For the term $\mathcal{V}_{\ell,m}(u, v)$, we focus for the moment on the case $m < \ell$ (our final conclusions below are true irrespective of this). At leading order we have

$$\begin{aligned}\hat{\varphi}_{t_0,t_\ell} &= \hat{\varphi}_{t_{m+1},t_\ell} \circ \left(\text{id} + \sum_{|a|=1} \tilde{K}_a(t_m) V_a + \cdots \right) \circ \hat{\varphi}_{t_0,t_m} \\ &= \text{id} + \sum_{|a|=1} \tilde{K}_a(t_m) V_a + \cdots,\end{aligned}$$

and

$$\begin{aligned}\hat{\varphi}_{t_{m+1},t_M} &= \hat{\varphi}_{t_{\ell+1},t_M} \circ \left(\text{id} + \sum_{|b|=1} \tilde{K}_b(t_\ell) V_b + \cdots \right) \circ \hat{\varphi}_{t_{m+1},t_\ell} \\ &= \text{id} + \sum_{|b|=1} \tilde{K}_b(t_m) V_b + \cdots.\end{aligned}$$

Substituting these expressions into the form for $\mathcal{V}_{\ell,m}(u, v)$ above we get

$$\begin{aligned}\mathcal{V}_{\ell,m}(u, v) &= \mathbb{E}(\tilde{K}_u(t_\ell)) \mathbb{E}(\tilde{K}_v(t_m)) (V_u \circ y_0)^\top (V_v \circ y_0) \\ &\quad + \sum_{|a|=1} \mathbb{E}(\tilde{K}_u(t_\ell)) \mathbb{E}(\tilde{K}_a(t_m) \tilde{K}_v(t_m)) (V_u \circ V_a \circ y_0)^\top (V_v \circ y_0) \\ &\quad + \sum_{|b|=1} \mathbb{E}(\tilde{K}_u(t_\ell) \tilde{K}_b(t_\ell)) \mathbb{E}(\tilde{K}_v(t_m)) (V_u \circ y_0)^\top (V_b \circ V_v \circ y_0) \\ &\quad + \sum_{\substack{|a|=1 \\ |b|=1}} \mathbb{E}(\tilde{K}_u(t_\ell) \tilde{K}_b(t_\ell)) \mathbb{E}(\tilde{K}_a(t_m) \tilde{K}_v(t_m)) (V_u \circ V_a \circ y_0)^\top (V_b \circ V_v \circ y_0).\end{aligned}$$

This breakdown allows us to categorize the different mechanisms through which local errors contribute to the global error at leading order. Indeed in the local flow remainder R we distinguish terms with:

(1) *zero expectation*: terms $\tilde{K}_w$ with $|w| = n + 1$ of zero expectation generate terms of order h^n in $\mathcal{E}^2$ through two routes, through $\mathcal{V}_{m,m}$ and the last term in the expression for $\mathcal{V}_{\ell,m}(u, v)$ just above. In $\mathcal{V}_{m,m}$ they generate order h^{n+1} terms, and the single sum over m means that their contribution to the global error $\mathcal{E}^2$ is order $Mh^{n+1} = \mathcal{O}(h^n)$. In the last term in $\mathcal{V}_{\ell,m}(u, v)$, they generate, when the expectations of the products indicated are non-zero, terms of order h^{n+2} ; the double sum over ℓ and m is then order h^n . Higher order terms $\tilde{K}_w$ with zero expectation simply generate a higher order contribution to the global error.

(2) *non-zero expectation*: terms $\tilde{K}_w$ with $|w| = n + 1$ of non-zero expectation will generate, through the first term in $\mathcal{V}_{\ell,m}(u, v)$, terms of order h^{n-1} —not consistent with an order $n/2$ integrator with global mean-square error of order h^n . If any such terms exist in R , their expectation must be included (which is a cheap additional computational cost) in the integrator, i.e. we should include $\mathbb{E}(\tilde{K}_w) V_w$ in $\hat{\psi}$. This will mean that the term left in R is $(\tilde{K}_w - \mathbb{E}(\tilde{K}_w)) V_w$ which has zero expectation and contributes to the global error through mechanism (1) above. Further, terms

$\tilde{K}_w$ with $|w| = n + 2$ of non-zero expectation will generate terms of order h^n in $\mathcal{E}^2$, i.e. they will also contribute at leading order through the first term in $\mathcal{V}_{\ell,m}(u, v)$.

The terms of non-zero expectation in R , which contribute at leading order to $\mathcal{E}^2$, either appear as natural next order terms or through the higher order terms $C_2(r\hat{\psi} + \hat{\psi}r)$ mentioned in the last section. We will see this explicitly in the Simulations section presently. We can, with a cheap additional computational cost, include them through their expectations in the integrators, so that when we compare their global errors, the corresponding terms left in the remainders have zero expectation and are higher order (and thus not involved in the comparison at leading order). Further, fortuitously, the terms of zero expectation which contribute in (1) through the last term in $\mathcal{V}_{\ell,m}(u, v)$ are exactly the same for the stochastic Taylor and sinh-log integrators. This is true at all orders and is a result of the following lemma, and that for the stochastic Taylor and sinh-log expansions when $|a| = 1$, then $\tilde{K}_a = J_a$.

Lemma 5.1. *Suppose $a, w \in \mathbb{A}^+$ and $|a| = 1$, then we have*

$$\mathbb{E}(J_a J_w) \equiv \frac{1}{2} \mathbb{E}(J_a (J_w - J_{\alpha \circ w})).$$

Proof. If $|w|$ is even, the expectations on both sides are zero. If $|w|$ is odd, in the shuffle products $a \sqcup w$ and $a \sqcup (\alpha \circ w)$, pair off terms where the letter a appears in the same position in an individual term of $a \sqcup w$ and the reverse of an individual term of $a \sqcup (\alpha \circ w)$. The pair, with the one-half factor, will have the same expectation as the corresponding term in shuffle product $a \sqcup w$. $\square$

(b) Simulations

We will demonstrate the properties we proved for the sinh-log series for numerical integration schemes of strong orders one and three-halves. We will consider a stochastic differential system with no drift, two driving Wiener processes and non-commuting governing *linear* vector fields $V_i \circ y \equiv a_i y$ for $i = 1, 2$.

We focus on the strong order one case first, and extend the analytical computations in Lord, Malham and Wiese (2008). With $n = 2$, and $C_1 = 1$ and $C_2 = -\frac{1}{2} + \epsilon$, the mean-square excess E , for general $\epsilon \in \mathbb{R}$, given by

$$E = h^3 ((U_{112} y_0)^T B(\epsilon) (U_{112} y_0) + (U_{221} y_0)^T B(\epsilon) (U_{221} y_0)).$$

Here $U_{112} = (a_1^2 a_2, a_1 a_2 a_1, a_2 a_1^2, a_2^3)^T$ and $U_{221} = (a_2^2 a_1, a_2 a_1 a_2, a_1 a_2^2, a_1^3)^T$ are both $4N \times N$ real matrices and the $4N \times 4N$ real matrix $B(\epsilon)$ consists of $N \times N$ blocks of the form $b(\epsilon) \otimes I_N$ (here $\otimes$ denotes the Kronecker product) where I_N is the $N \times N$ identity matrix and $b(\epsilon)$ is

$$\begin{pmatrix} \frac{5}{24} - (\epsilon - \frac{1}{4})(3\epsilon - \frac{5}{12}) & -\epsilon(3\epsilon - \frac{11}{12}) & -(\epsilon - \frac{1}{4})(3\epsilon - \frac{5}{12}) & -3\epsilon(3\epsilon - \frac{5}{12}) \\ -\epsilon(3\epsilon - \frac{11}{12}) & -\epsilon(3\epsilon - \frac{2}{3}) & -\epsilon(3\epsilon - \frac{11}{12}) & -\epsilon(3\epsilon - \frac{1}{2}) \\ -(\epsilon - \frac{1}{4})(3\epsilon - \frac{5}{12}) & -\epsilon(3\epsilon - \frac{11}{12}) & \frac{5}{24} - (\epsilon - \frac{1}{4})(3\epsilon - \frac{5}{12}) & -3\epsilon(3\epsilon - \frac{5}{12}) \\ -3\epsilon(3\epsilon - \frac{5}{12}) & -\epsilon(3\epsilon - \frac{1}{2}) & -3\epsilon(3\epsilon - \frac{5}{12}) & -5\epsilon(3\epsilon - 1) \end{pmatrix}.$$

Each of the eigenvalues of $b(\epsilon)$ are N multiple eigenvalues for $B(\epsilon)$. The eigenvalues of $b(\epsilon)$ are shown in Figure 1. The sinh-log expansion corresponds to $\epsilon = 0$, while the exponential Lie series corresponds to $\epsilon = \frac{1}{6}$. The eigenvalues of $b(0)$ are $\frac{5}{24}$ and zero (thrice)—confirming our general result for the sinh-log expansion. However,




Figure 1. The eigenvalues, $\lambda_i(\epsilon)$, $i = 1, \dots, 4$ of matrix $b(\epsilon)$, as a function of ϵ .

the eigenvalues of $b(\frac{1}{6})$ are $\frac{5}{24}$, 0.5264, 0.1667 and -0.0264 . One negative eigenvalue means that there are matrices a_1 and a_2 and initial conditions y_0 for which the order one stochastic Taylor method is more accurate, in the mean-square sense, than the exponential Lie series method (for linear vector fields we also call this the Magnus method). From Figure 1, we deduce that for any small values of ϵ away from zero, we cannot guarantee $E > 0$ for all possible governing vector fields and initial data. The strong order one sinh-log integrator is optimal in this sense. This is also true at the next order from Corollary 4.2.

For our simulations we take $N = 2$ and set the coefficient matrices to be

$$a_1 = \begin{pmatrix} 0.105 & -7.43 \\ 0.03 & 0.345 \end{pmatrix} \quad \text{and} \quad a_2 = \begin{pmatrix} -0.065 & -9.44 \\ -0.005 & 0.265 \end{pmatrix}.$$

In Figure 2, using these matrices, we plot the mean-square excess E^{ls} for the exponential Lie series and E^{sl} for the sinh-log series, as a function of the two components of y_0 . We see there are regions of the phase space where E^{ls} is negative—of course E^{sl} is positive everywhere. Hence if the solution y_t of the stochastic differential system governed by the vectors fields $V_i \circ y = a_i y$, $i = 1, 2$, remains in the region where E^{ls} is negative, then the numerical scheme based on the order one exponential Lie series is less accurate than the stochastic Taylor method. Note that for the stochastic Taylor method, we need to include the terms

$$\frac{1}{8}h^2(a_1^4 + a_1^2 a_2^2 + a_2^2 a_1^2 + a_2^4)$$

in the integrator. These are the expectation of terms with $|w| = 4$ which contribute at leading order in the global error (only), and which can be cheaply included in the stochastic Taylor integrator. For the exponential Lie series we include the terms

$$\frac{1}{24}h^2([a_2, [a_2, a_1]]a_1 + [a_1, [a_1, a_2]]a_2 + a_2[a_1, [a_1, a_2]] + a_1[a_2, [a_2, a_1]]),$$

in $\hat{\psi}^{\text{ls}}$. These are non-zero expectation terms with $|w| = 4$ which contribute at leading order in the global error through $-C_2(r\hat{\psi} + \hat{\psi}r)$, where $C_2 = -\frac{1}{2}$. In the




Figure 2. Contour plots of the mean-square excess as a function of the two components of the data $y_0 = (u_0, v_0)^T$, for the strong order one example, for the exponential Lie series (left panel) and the sinh-log series (right panel).

same vein, for the sinh-log integrator, we include in $\hat{\psi}^{\text{sl}}$ the terms

$$\frac{1}{4}h^2(2a_1^4 + a_2^2a_1^2 + a_2a_1^2a_2 + a_1a_2^2a_1 + a_1^2a_2^2 + 2a_2^4).$$

Figure 3 shows the global error versus time for all three integrators for the linear system. We used the global interval of integration $[0, 0.0002]$, starting with $y_0 = (19.198, 28.972)^T$, and stepsize $h = 2.5 \times 10^{-5}$. With this initial data, the small global interval of integration means that all ten thousand paths simulated stayed within the region of the phase space where E^{ls} is negative in Figure 2.

The error for the exponential Lie series integrator, we see in Figure 3, is larger than that for the stochastic Taylor integrator. The error for the sinh-log integrator is smaller, though only marginally so. In fact it is hardly discernible from the stochastic Taylor plot, so the middle panel shows a magnification of the left region of the plot in the top panel. We plot the differences between the errors in the lower panel to confirm the better performance of the sinh-log integrator over the global interval. Further, estimates for the local errors for the sinh-log and Lie series integrators from the data in Figure 3, of course, quantitatively match analytical estimates for the mean-square excess E above.

Remark 5.1. Generically the Castell–Gaines method of strong order one markedly outperforms the sinh-log method (which itself outperforms the stochastic Taylor method more markedly). However, as we have seen, there are pathological cases for which this is not true.

In Figure 4 we compare the global errors for the strong order three-halves sinh-log and stochastic Taylor methods, with governing linear vector fields with coefficient matrices

$$a_1 = \begin{pmatrix} 0 & 1 \\ -1/2 & -51/200 \end{pmatrix} \quad \text{and} \quad a_2 = \begin{pmatrix} 1 & 1 \\ 1 & 1/2 \end{pmatrix}.$$

and initial data $y_0 = (1, 1/2)^T$. Again as expected we see that the stochastic Taylor method is less accurate than the sinh-log method for sufficiently small stepsizes.




Figure 3. Mean-square global error vs time plot for the sinh-log, exponential Lie (Magnus) and stochastic Taylor methods for the order one example. The top panel shows the error, and the middle panel a magnification of the left region of the plot in the top panel. The lower panel shows the differences between, the global sinh-log and exponential Lie errors, and the error of stochastic Taylor method.

Remark 5.2. There is one caveat we have not mentioned thusfar. Constructing the approximation $\hat{\varphi}_t$ from $\hat{\psi}_t$ is in general nontrivial. For linear vector fields $V_i \circ y = a_i y$, we know that $\hat{\psi}_t$ is simply a matrix, and we can straightforwardly construct $\hat{\varphi}_t$ using the matrix square root. For general nonlinear vector fields, we have not




Figure 4. Global error vs stepsize plot for the sinh-log and stochastic Taylor methods of strong order three-halves example.

as yet found a superior method to simply expanding the square root shown to a sufficient number of high degree terms.

6. Concluding remarks

We have shown that the mean-square remainder associated with the sinh-log series is always smaller than the corresponding stochastic Taylor mean-square remainder, when there is no drift, to all orders. Since the order one-half sinh-log numerical method is the same as the order one-half Castell–Gaines method, it trivially inherits the asymptotically efficient property as well (indeed, if we include a drift term as well). We have not endeavoured to prove asymptotic efficiency more generally. However, in Section 5 we demonstrated that for two driving Wiener processes, the order one sinh-log numerical method is optimal in the following sense. From Figure 1, we see that any deviation of ϵ from zero will generate a negative eigenvalue for $b(\epsilon)$. Consequently there exist vector fields such that the mean-square excess will be negative in regions of the phase space. Further, from Corollary 4.2, the order three-halves sinh-log integrator is also optimal in this sense. These results are only true when there is no drift, and it could be argued that our simulations and demonstrations are somewhat academic. However the results we proved have application in splitting methods for stochastic differential equations. For example, in stochastic volatility simulation in finance, Ninomiya & Victoir (2006) and Halley, Malham & Wiese (2008) simulate the Heston model for financial derivative pricing, and use splitting to preserve positivity for the volatility numerically. They employ a Strang splitting that separates the diffusion flow from the drift flow and requires a distinct simulation of the purely diffusion governed flow.

Why is the sinh-log expansion the answer? This result is intimately tied to the mean-square error measure we chose. The terms in the remainder of any truncation contain multiple Stratonovich integrals. Associated with each one is a mean-square error. There is a structure underlying these expectations. The sinh-log expansion somehow encodes this structure in an optimal form, it emulates the stochastic Taylor information more concisely. The next question is of course, what is the best structure when we include drift? Answering this is our next plan of action.

We would like to thank Peter Friz, Terry Lyons and Hans Munthe-Kaas for interesting and useful discussions related to this work. We would also like to thank the anonymous referees for their critique and suggestions which helped improve the original manuscript.

References

- Azencott, R. 1982 Formule de Taylor stochastique et développement asymptotique d'intégrales de Feynman, Seminar on Probability XVI, *Lecture Notes in Math.* **921**, Springer, 237–285
- Baudoin, F. 2004 *An introduction to the geometry of stochastic flows* Imperial College Press (2004)
- Ben Arous, G. 1989 Flots et series de Taylor stochastiques, *Probab. Theory Related Fields* **81**, 29–77
- Burrage, K. & Burrage, P. M. 1999 High strong order methods for non-commutative stochastic ordinary differential equation systems and the Magnus formula, *Phys. D* **133**, 34–48
- Castell, F. 1993 Asymptotic expansion of stochastic flows, *Probab. Theory Related Fields* **96**, 225–239
- Castell, F. & Gaines, J. 1995 An efficient approximation method for stochastic differential equations by means of the exponential Lie series, *Math. Comp. Simulation* **38**, 13–19
- Chen, K. T. 1957 Integration of paths, geometric invariants and a generalized Baker–Hausdorff formula, *Annals of Mathematics* **65**(1), 163–178
- Connes, A. & Kreimer, D. 1998 Hopf algebras, renormalization and noncommutative geometry, *Commun. Math. Phys.* **199**, 203–242
- Connes, A. & Moscovici, H. 1998 Cyclic cohomology and the transverse index theorem, *Commun. Math. Phys.* **198**, 198–246
- Ebrahimi-Fard, K. & Guo, L. 2006 Mixable shuffles, quasi-shuffles and Hopf algebras, *Journal of algebraic combinatorics* **24**(1), 83–101
- Fleiss, M. 1981 Fonctionnelles causales non linéaires et indéterminées non-commutatives, *Bulletin de la Société Mathématique de France* **109**, 3–40
- Gaines, J. 1994 The algebra of iterated stochastic integrals, *Stochastics and Stochastics Reports* **49**, 169–179
- Halley, W., Malham, S.J.A. & Wiese, A. 2008 Positive stochastic volatility simulation, arXiv: 0802.4411.v1
- Iserles, A. 2002 Expansions that grow on trees, *Notices of the AMS* **49**(4)
- Kawski, M. 2001 The combinatorics of nonlinear controllability and noncommuting flows, Lectures given at the Summer School on Mathematical Control Theory, Trieste
- Kloeden, P.E. & Platen, E. 1999 *Numerical solution of stochastic differential equations*, Springer
- Kunita, H., 1980 On the representation of solutions of stochastic differential equations, *Lecture Notes in Math.* **784**, Springer-Verlag, 282–304
- Li, C.W. & Liu, X.Q. 2000 Almost sure convergence of the numerical discretization of stochastic jump diffusions, *Acta. App. Math.* **62**, 225–244
- Lord, G., Malham, S.J.A. & Wiese, A. 2008 Efficient strong integrators for linear stochastic systems, *SIAM J. Numer. Anal.* **46**(6), 2892–2919
- Lyons, T. 1998 Differential equations driven by rough signals, *Rev. Mat. Iberoamericana* **14**(2), 215–310
- Lyons, T., Caruana, M. & Lévy, T. 2007 Differential equations driven by rough paths. École d'Été de Probabilités de Saint-Flour XXXIV-2004, Lecture Notes in Mathematics 1908, Springer

- Lyons, T. & Victoir, N. 2004 Cubature on Wiener space, *Proc. R. Soc. Lond. A*, **460**, 169–198
- Magnus, W. 1954 On the exponential solution of differential equations for a linear operator, *Comm. Pure Appl. Math.* **7**, 649–673
- Malham, S.J.A., Wiese, A. 2008 Stochastic Lie group integrators, *SIAM J. Sci. Comput.* **30**(2), 597–617
- Manchon, D. & Paycha, S. 2007 Shuffle relations for regularised integrals of symbols, *Communications in Mathematical Physics* **270**(1), 13–51
- Munthe-Kaas, H.Z. & Wright, W.M. 2007 On the Hopf algebraic structure of Lie group integrators, *Foundations of Computational Mathematics* **8**(2), 227–257
- Murua, A. 2006 The Hopf algebra of rooted trees, free Lie algebras, and Lie series, *Foundations of Computational Mathematics* **6**(4), 387–426
- Newton, N.J. 1991 Asymptotically efficient Runge–Kutta methods for a class of Itô and Stratonovich equations, *SIAM J. Appl. Math.* **51**, 542–567
- Ninomiya, S. & Victoir, N. 2006 Weak approximation of stochastic differential equations and application to derivative pricing, arXiv:math/0605361v3
- Reutenauer, C. 1993 *Free Lie algebras*, London Mathematical Society Monographs New Series 7, Oxford Science Publications
- Strichartz, R.S. 1987 The Campbell–Baker–Hausdorff–Dynkin formula and solutions of differential equations, *J. Funct. Anal.* **72**, 320–345
- Varadarajan, V. S. 1984 *Lie groups, Lie algebras, and their representations*, Springer
- Wiktorsson, M. 2001 Joint characteristic function and simultaneous simulation of iterated Itô integrals for multiple independent Brownian motions, *Ann. Appl. Probab.* **11**(2), 470–487